

| Specification | | | | | |
|---|-----------------|-------|-------|-------|-------|
| Z5 Competition Brushless Motor MOD Edition | 21.5T | 17.5T | 13.5T | 11.5T | 10.5T |
| Item NO. (商品编码) | 53653 | 53652 | 53651 | 53650 | 53649 |
| KV(RPM/V) (KV值) | 1510 | 1860 | 2380 | 2790 | 3050 |
| Weight(g) (重量) | 169 | 170 | 170 | 169 | 170 |
| Resistance(Ri)(mOhm) (电阻) | 76.8 | 50 | 32.2 | 22.7 | 18.4 |
| Peak Watts(峰值功率) | 120 | 156 | 234 | 260 | 282 |
| Max Efficiency (最大效率) | 93% | 93% | 93% | 92% | 92% |
| Valtage Input (输入电压) | 3.7V-11.1V LiPo | | | | |
| Rotor Diameter (转子直径) | 12.5mm | | | | |

| Specification | | | | | |
|---|----------------|-------|-------|-------|-------|
| Z5 Competition Brushless Motor MOD Edition | 9.5T | 8.5T | 7.5T | 6.5T | 6.0T |
| Item NO. (商品编码) | 53648 | 53647 | 53646 | 53645 | 53776 |
| KV(RPM/V) (KV值) | 3350 | 3730 | 4250 | 4840 | 5480 |
| Weight(g) (重量) | 170 | 170 | 168 | 169 | 169 |
| Resistance(Ri)(mOhm) (电阻) | 15.3 | 12.5 | 10.1 | 7.6 | 6.4 |
| Peak Watts(峰值功率) | 298 | 322 | 391 | 449 | 467 |
| Max Efficiency (最大效率) | 92% | 92% | 92% | 91% | 91% |
| Valtage Input (输入电压) | 3.7V-7.4V LiPo | | | | |
| Rotor Diameter (转子直径) | 12.5mm | | | | |

| Specification | | | | | | |
|---|----------------|-------|-------|-------|-------|-------|
| Z5 Competition Brushless Motor MOD Edition | 5.5T | 5.0T | 4.5T | 4.0T | 3.5T | 3.0T |
| Item NO. (商品编码) | 53644 | 53643 | 53642 | 53641 | 53640 | 53639 |
| KV(RPM/V) (KV值) | 5580 | 5900 | 6520 | 7200 | 8200 | 9400 |
| Weight(g) (重量) | 170 | 170 | 172 | 170 | 168 | 165 |
| Resistance(Ri)(mOhm) (电阻) | 5.4 | 4.6 | 3.7 | 3.2 | 2.4 | 2 |
| Peak Watts(峰值功率) | 483 | 541 | 610 | 656 | 713 | 770 |
| Max Efficiency (最大效率) | 91% | 91% | 90% | 90% | 88% | 85% |
| Valtage Input (输入电压) | 3.7V-7.4V LiPo | | | | | |
| Rotor Diameter (转子直径) | 13.0mm | | | | | |